

# 8 CH D1 REAL-TIME DVR

SA-8200HDP

D1



## Specifications

<b>MODEL</b>		SA-8200HDP
<b>System</b>	<b>Compression Format</b>	Baseline H.264
	<b>OS</b>	Embedded Linux
<b>Video</b>	<b>Input</b>	8CH Standard BNC
	<b>Standard Output</b>	VGA, CVBS(Spot)
	<b>Advanced Output</b>	HDMI
<b>Audio</b>	<b>Input</b>	1CH
	<b>Output</b>	1CH
	<b>Two way audio</b>	Yes
<b>Recording</b>	<b>Real-Time Recording</b>	8CH D1 Real-Time
	<b>1080P HD-SDI</b>	No
	<b>720P HD-SDI</b>	No
	<b>960H</b>	120FPS (NTSC)/100FPS (PAL)
	<b>D1</b>	240FPS (NTSC)/200FPS (PAL)
	<b>CIF</b>	240FPS (NTSC)/200FPS (PAL)
	<b>Recording Mode</b>	Schedule, Manual, Motion
<b>Playback</b>	<b>Playback Channel</b>	8CH
	<b>Search Mode</b>	Time, Event, File Management
<b>Backup</b>	<b>USB</b>	1 USB2.0 port
	<b>DVD Burner</b>	No
	<b>Backup Format</b>	DAT or AVI
<b>Remote Application</b>	<b>Dual Stream</b>	Master Stream 1-25/30FPS@960H, Sub-Stream 1-12/15FPS@CIF
	<b>Browser</b>	IE, Chrome, Safari, Firefox (Mac OS, Windows XP/Vista/7/8)
	<b>Master Stream in Network</b>	Yes
	<b>CMS</b>	Yes
	<b>3G</b>	Provision CAM for iOS/Android Phones/Provision HD for iOS/Android Tablets
	<b>User Access</b>	18 Users Online with Professional Authority Management
<b>Alarm</b>	<b>Input</b>	No
	<b>Output</b>	No
<b>Storage</b>	<b>HDD</b>	1SATA (3TB)
	<b>E-SATA</b>	No
<b>PTZ</b>	<b>Connection</b>	No
	<b>Supported Protocol</b>	No
	<b>Supported Controls</b>	No
<b>Network</b>	<b>Ethernet</b>	100 Mbps (RJ-45)
	<b>Protocol</b>	TCP/IP, DHCP, DDNS, NTP, SMTP
<b>Others</b>	<b>Dimension</b>	201(W) x 210(D) x 47(H) mm
	<b>IR Controller</b>	Yes
	<b>Power Supply</b>	DC12V/2A
	<b>Operating Temperature</b>	0°C ~50°C